


CAN J1939 SETTINGS (Not programmable)		
BAUDRATE	250kb/s	
START DELAY	2s	
CYCLE RATE	50ms	
SOURCE ADDRESS	130 (82h)	
ID	0CF00382h	
COMMANDED ADDRESS	Disabled	
EEC2	SPN91	0 - 100%
	SPN558	1 - 0 (7%)
DTC	DM1	Enabled
SOFTWARE: 962845M010-SW01		



Wire side view

PIN N°	DESCRIPTION
1	CAN HIGH
2	CAN SHIELD
3	0V GROUND
4	CAN LOW
5	-
6	+8.. 32VDC

Connector : AMP Nr. 1-967616-1
 Terminals : AMP Nr. 0-0962885-5
 Wire seal : AMP Nr. 0-0967067-1
 Blind Plug : AMP Nr. 0-0967056-1
 Not Included

	Date	Name	Signature / Stamp
Drawing /... /.....		
Customer validation /... /.....		
Prototype /... /.....		
Customer validation /... /.....		

UNLESS OTHERWISE SPECIFIED:
 DIMENSIONS ARE IN mm
 TOLERANCES:
 ISO 2768 - vL

TITLE: Throttle Pedal 45°
 CAN J1939

	NAME	CREATED DATE
DRAWN	JST	26/09/2023
CHK'D	SB	26/09/2023

MCS
 MOBILE CONTROL SYSTEMS SA
 This drawing is confidential and remains the sole property of Mobile Control Systems S.A. This document is protected in accordance with the prevailing law.

PART NR:

962 845 M010

REV: **A**
 SCALE: 1:2
 SHEET 1 OF 1