


uControl[™] SERIES

Rugged Machine Controllers

Get the most out of any application with powerful, flexible and precise controllers. Featuring multiple CAN interfaces, extensive outputs and an available high-current output option, the complete family of uControl mobile machine controllers can handle any job, big or small.




MC4-26-20

INPUTS	
UNIVERSAL ANALOG / HIGH FREQUENCY	10
UNIVERSAL ANALOG	16
TOTAL INPUTS	26

OUTPUTS (SOFTWARE SELECTABLE)		
4A PWM (FEEDBACK)	10	
DUAL-RANGE PWM 4A / 0.5 A (FEEDBACK)	10	
15A PWM (FEEDBACK)	-	
TOTAL OUTDUTS	20	

OTHER	
CAN 2.0B / J1939	3 Channels
SENSOR SUPPLY	(2) 400mA max @ 5 or 10 VDC [Software Selectable Voltage]
CONNECTORS	J1A (4 pin) - DTP06-4S J1B (6 pin) - DT06-6S-E008 J2 (18 pin - A key) - DT16-18SA-K004 J3 (18 pin - B key) - DT16-18SB-K004 J4 (18 pin - C key) - DT16-18SC-K004
LED INDICATORS	(1) Green - Power Status (1) White - Software Configurable (1) Blue - Software Configurable
DIMENSIONS	10.09 x 5.45 x 2.38 in (256.2 x 138.5 x 60.4 mm)

INPUT OPTIONS (ALL CONTROLLERS)



MC4-21-14-H8

INPUTS	
UNIVERSAL ANALOG / HIGH FREQUENCY	8
UNIVERSAL ANALOG	13
TOTAL INPUTS	21

OUTPUTS (SOFTWARE SELECTABLE)		
4A PWM (FEEDBACK)	6	
DUAL-RANGE PWM 4A / 0.5 A (FEEDBACK)	8	
15A PWM (FEEDBACK)	8	
TOTAL OUTPUTS	22	

OTHER	
CAN 2.0B / J1939	3 Channels
SENSOR SUPPLY	(2) 400mA max @ 5 or 10 VDC [Software Selectable Voltage]
CONNECTORS	J1A (4 pin) - DTP06-4S J1B (6 pin) - DT06-6S-E008 J2 (18 pin - A key) - DT16-18SA-K004 J3 (18 pin - B key) - DT16-18SB-K004 J4 (18 pin - D key) - DT16-18SD-K004
LED INDICATORS	(1) Green - Power Status (1) White - Software Configurable (1) Blue - Software Configurable (8) Green - High Current Status • Solid - Output Active • Dark - Output Inactive • Blinking - Output in Fault
DIMENSIONS	10.09 x 5.45 x 2.38 in (256.2 x 138.5 x 60.4 mm)

	•	,			
ANALOG FUNCTION	N .			DIGITAL MODE	
ADC RESOLUTION	1	2 bits		TYPE	Low/High Side (Software Configurable)
ACCURACY	0-5 VDC Mode: All Other Modes	Typical +/- 0.2 % FS s: Typical +/- 1 % FS			Nominally 10 kΩ
	Voltage Mode	Current Mode	Resistive Mode	INPUT IMPEDANCE	(Configuration Dependent)
MEASURING RANGES	0 to 5V 0 to 36V	0 to 22 mA	100Ω to 100 kΩ	SAMPLING FREQUENCY	250 Hz
	(Absolute / Ratio-metric)	0 to 22 mA 100Ω to 100 kL	1000 to 100 k0	SWITCH-ON LEVEL	Software Configurable
INPUT RESISTANCE	10kΩ +/- 20%	200Ω	20kΩ	SWITCH-OFF LEVEL	from 0 to 36V
SAMPLING FREQUENCY		1kHz			

HIGH FREQUENCY	MODE
TYPE	Single ended, digital low/high side (Software Configurable)
INPUT IMPEDANCE	Nominally 10 $k\Omega$ (Configuration Dependent)
INPUT FREQUENCY	1Hz50kHz
THRESHOLD 1	Standard switch on at 2.5 V / Standard switch off at 1.25 V
THRESHOLD 2	Standard switch on at 7.5 V / Standard switch off at 3.75 V



MC2-18-6 Coming Soon

INPUTS	
UNIVERSAL ANALOG / HIGH FREQUENCY	4
UNIVERSAL ANALOG	14
TOTAL INPUTS	18

OUTPUTS (SOFTWARE SELECTABLE)	
4A PWM (FEEDBACK)	2
DUAL-RANGE PWM 4A / 0.5 A (FEEDBACK)	4
15A PWM (FEEDBACK)	-
TOTAL OUTPUTS	6

OTHER	
CAN 2.0B / J1939	2 Channels
SENSOR SUPPLY	(1) 400mA max @ 5 or 10 VDC [Software Selectable Voltage]
CONNECTORS	J1 (18 pin - E key) - DT16-18SE-K004 J2 (18 pin - B key) - DT16-18SB-K004
LED INDICATORS	(1) Green - Power Status(1) White - Software Configurable(1) Blue - Software Configurable
DIMENSIONS	5.60 x 5.44 x 2.38 in (142.3 x 138.3 x 60.4 mm)

MC3-21-10 Coming Soon

INPUTS	
UNIVERSAL ANALOG / HIGH FREQUENCY	8
UNIVERSAL ANALOG	13
TOTAL INPUTS	21

OUTPUTS (SOFTWARE SELECTABLE)		
4A PWM (FEEDBACK)	6	
DUAL-RANGE PWM 4A / 0.5 A (FEEDBACK)	4	
15A PWM (FEEDBACK)	-	
TOTAL OUTPUTS	10	

OTHER	
CAN 2.0B / J1939	3 Channels
SENSOR SUPPLY	(1) 400mA max @ 5 or 10 VDC [Software Selectable Voltage]
CONNECTORS	J1A (4 pin) - DTP06-4S J1B (6 pin) - DT06-6S-E008 J2 (18 pin - A key) - DT16-18SA-K004 J3 (18 pin - B key) - DT16-18SB-K004
LED INDICATORS	 Green - Power Status White - Software Configurable Blue - Software Configurable
DIMENSIONS	7.85 x 5.44 x 2.38 in (199.3 x 138.3 x 60.4 mm)

OUTPUT OPTIONS (BY TYPE)

	4A BINARY (FEEDBACK)	4A PWM (FEEDBACK)	DUAL-RANGE PWM 4A / 0.5A (FEEDBACK)	15A [SINGLE] / 25A [PARALLEL] PWM (FEEDBACK)
TYPE	Low/High side, H-bridge (Software configurable as push/pull or float)			
PWM FREQUENCY			50 – 5 kHz	50 – 2 kHz
DITHER FREQUENCY			Configurable	
DITHER AMPLITUDE			Configurable	
CONTROL RANGE	N/A	0.05 - 4A	Low Current Mode: 0.005 – 0.5A High Current Mode: 0.05 - 4A (software configurable)	0.1A – 15A 0.1A – 25A (if in parallel with high side channel)
CONTROL RESOLUTION		1 mA	Low Current Mode: 1mA Hight Current Mode: 1 mA (software configurable)	20mA
FLY BACK PROTECTION			Integrated	
DUTY CYCLE RESOLUTION			.01% @ 250Hz	
MAX AMPERAGE	4A		15A (Parallel with mated high side driver for 25A)	
OUTPUT INDICATION	N/A		LED with output state & fault state Single Red LED per output	
DIAGNOSTICS	Open/Short Circuit Protection			
FAULT MODES			Short circuit, overcurrent and open circuit protection	on

SERIES SPECIFICATIONS

COMPUTING	
PROCESSOR	Renesas® Super H 72546 @ 200 MHz (32-bit)
FLASH	3.75 MB (1,000 writes)
SRAM	256 KB
MRAM	32 KB
EEPROM	128 KB

ENVIRONMENTAL	
OPERATING TEMPERATURE	-40° to +221°F (-40° to +105°C)
STORAGE TEMPERATURE	-40° to +257°F (-40° to +125°C)
OPERATING ALTITUDE	0 - 4000 meters
PROTECTION	IP67, IP69K with Protective Boot
HOUSING	Cast aluminum housing, soft-gel potted for extreme ruggedness and durability

POWER SUPPLY	
SUPPLY VOLTAGE	6-32 VDC, Nominal Operation @ 12 /24 VDC
PEAK SUPPLY VOLTAGE	36 VDC
MAXIMUM CURRENT (MC3/MC4)	50 A (25 A with only 1 Power / 1 GND connected)
MAXIMUM CURRENT (MC4-H8)	100A
IDLE CURRENT 12/24 VDC	< 200mA @ 12VDC < 100mA @ 24VDC
STANDBY CURRENT 12/24 VDC	< 5mA @12VDC < 2.5mA @ 24VDC
SLEEP PIN	Control sleep and wake functionality

MECHANICAL TESTING		
IP6X	IEC 60529 Section 14.2.6, SAE J1455, Section 4.7.3	
IPX7	IEC 60529 Section 14.2.7	
IPX9K	IEC 60529, Section 14.2.9 (with protective boot)	
VIBRATION	J1455 Section 4.10.4.1/5.82Grms, 8 hours per axis	
SHOCK	J1455 Section 4.10.4/6+/-pulses, 50 G's, 6 ms	
FLUID COMPATIBILITY	J1455 Section 4.4.3	
HANDLING DROP TEST	J1455 Section 4.11.3.1, 1-meter drop on concrete on each of 6 box faces	
SALT FOG	ASTM-B117/96 Hours at 35°C 5% NaCl	
HUMIDITY / TEMPERATURE	SAE J1455 4.2.3 with reference to ISO 15998-7.2.2 for temperature & humidity levels	

IP.	CE	e-Mark Pending	ISO-13766
69K	Pending	REAC	H / RoHS

ELECTRICAL TESTING	
2004/108/EC (E-MARK)*	Broadband radiated emissions [ref. CISPR 25 sec 6.4], Conducted immunity [ref. ISO 7637-2], Conducted emissions [ref. ISO 7637-2], Narrowband radiated emissions, Radiated immunity [ref. ISO11452-2]
CISPR 11*	Radiated emissions [ref. CISPR 16-1]
CISPR 25*	Conducted emissions (power lines), Conducted emissions (signal lines), Radiated emissions
EN 60945*	Conducted emissions [ref. CISPR 16-1], Conducted immunity (RF disturbance) [ref. EN 61000-4-6], ESD immunity [ref. EN 61000-4-2]
EN 61000-4-2*	ESD immunity, 8kV contact & 16 kV air. Response level I.
EN 61326-1*	Radiated immunity [ref. EN 61000-4-3], Conducted immunity (fast transients on power & signal lines) [ref. EN 61000-4-4], Conducted immunity (surges on power lines) [ref. EN 61000-4-5], Magnetic immunity [ref. EN 61000-4-8]
SAE J1113-2*	Conducted immunity (power leads) [ref. MIL-STD0461F]
SAE J1113-4*	Conducted immunity (BCI) [ref. ISO 11452-4]
SAE J1113-11*	Conducted immunity (transients on power leads) [ref. ISO 7637-2], 5 pulses of 174V for 350 mS with 4Ω source impedance. Severity level 4, response I.
SAE J1113-12*	Conducted immunity (coupling clamp on signal lines) [ref. ISO 7637-3]
SAE J1113-13*	ESD immunity [ref. ISO 10605]
SAE J1113-21*	Radiated immunity (absorption lined chamber) [ref. ISO 11452-2] >150 V/m (200MHz -3.2GHz)
SAE J1113-22*	Radiated immunity (magnetic fields) [ref. MIL-STD-461F]
SAE J1113-26*	Radiated immunity (ac electric fields – power lines)
SAE J1455*	Inductive switching, 10 sequential 28V +/-600 V pulses of 1ms duration on I/O lines
SHORT CIRCUIT PROTECTION	Internal testing where power outputs, signal lines, all inputs and powered outputs are shorted to Vbat and then ground for one minute each.
SUPPLY VOLTAGE VARIATION	Internal testing suite (dropouts, dips, random bounce, engine cranking). Reverse voltage test is -32 V for one minute.
EXTREME TEMPERATURES	Internal testing of powerup and 24-hour operation at -40° C and 85° C

^{*} Pending Final Testing

SOFTWARE OPTIONS		
ACE™	Created by Enovation Controls, ACE is a powerful and easy-to-learn configuration tool to simplify and speed up control system development. ACE was designed for both machine experts with no coding experience and experienced programmers looking for a more efficient way to work.	
CODESYS	For users experienced with controller programming, uControl mobile machine controllers support CODESYS for development.	


▲ CALIFORNIA PROP65 WARNING: This product can expose you to chemicals known to the State of California to cause cancer. For more information, go to www.P65Warnings.ca.gov

1900103 09-2021



CONTACT

sales@enovationcontrols.com



CORPORATE HEADQUARTERS

5311 S 122nd E Ave Tulsa, Oklahoma, USA 74146

United States • United Kingdom • India • China

